

Crestron:

TO USE A ZAPPITI 4K PLAYER WITH CRESTRON SIMPL WINDOWS

1. TCP/IP CONNECTION REQUIRED WITH PORT SET TO 8080d
2. Serial i/o using the following commands

Please replace "192.168.1.69" with the IP address of your Zappiti 4K HDR:

GET /remoteCmd?id=0&command=POWER http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=MENU http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=BACK http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=LEFT http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=RIGHT http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=UP http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=DOWN http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=SETUP http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=OK http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=HOME http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=PLAY http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=FR http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=FF http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=PREV http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=NEXT http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=VOL_UP http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=VOL_DOWN http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=VOL_MUTE http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=INFO http/1.1\x0D\x0AHOST:

192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_0 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_1 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_2 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_3 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_4 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_5 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_6 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_7 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_8 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A

GET /remoteCmd?id=0&command=I KEYCODE_9 http/1.1\x0D\x0AHOST:
192.168.1.69\x0D\x0A\x0D\x0A